

00/90/60

09-07-00

A

HEWLETT-PACKARD COMPANY

PATENT APPLICATION

Intellectual Property Administration
P. O. Box 272400
Fort Collins, Colorado 80528-9599

ATTORNEY DOCKET NO. 10001963-7

IN THE U.S. PATENT AND TRADEMARK OFFICE
Patent Application Transmittal Letterjcs13 U.S. P.
09/06/00
09/06/00ASSISTANT COMMISSIONER FOR PATENTS
Washington, D.C. 20231

Sir:

Transmitted herewith for filing under 37 CFR 1.53(b) is a(n): ☒ Utility ☐ Design☒ original patent application,
☐ continuation-in-part application

INVENTOR(S): Oscar R Herrera E.

TITLE: Multiple Output Node Charge Coupled Device

Enclosed are:

- (X) The Declaration and Power of Attorney. ☒ signed ☐ unsigned or partially signed
(X) 3 sheets of drawings (one set) ☐ Associate Power of Attorney
☐ Form PTO-1449 ☐ Information Disclosure Statement and Form PTO-1449
☐ Priority document(s) ☐ (Other) _____ (fee \$ _____)

CLAIMS AS FILED BY OTHER THAN A SMALL ENTITY

(1) FOR	(2) NUMBER FILED	(3) NUMBER EXTRA	(4) RATE	(5) TOTALS
TOTAL CLAIMS	12 — 20	0	X \$18	\$ 0
INDEPENDENT CLAIMS	3 — 3	0	X \$78	\$ 0
ANY MULTIPLE DEPENDENT CLAIMS	0		\$260	\$ 0
BASIC FEE: Design \$310.00 ; Utility \$690.00				\$ 690
TOTAL FILING FEE				\$ 690
OTHER FEES				\$
TOTAL CHARGES TO DEPOSIT ACCOUNT				\$ 690

Charge \$ 690 to Deposit Account 08-2025. At any time during the pendency of this application, please charge any fees required or credit any over payment to Deposit Account 08-2025 pursuant to 37 CFR 1.25. Additionally please charge any fees to Deposit Account 08-2025 under 37 CFR 1.16, 1.17, 1.19, 1.20 and 1.21. A duplicate copy of this sheet is enclosed.

"Express Mail" label no. EL634216325USDate of Deposit 9/6/00

I hereby certify that this is being deposited with the United States Postal Service "Express Mail Post Office to Addressee" service under 37 CFR 1.10 on the date indicated above and is addressed to: Assistant Commissioner for Patents, Washington, D.C. 20231.

By CRISSE J. SALAZAR

Typed Name: Crissy J. Salazar

Respectfully submitted,

Oscar R Herrera E.

By Steven L Webb

Steven L Webb

Attorney/Agent for Applicant(s)

Reg. No. 44,395

Date: 9/6/00

Telephone No.: (970) 898-7745

"Express Mail" mailing label number EL634216325US

Date of Deposit 9-6-00

I hereby certify that this paper or fee is being deposited with the United States Postal Service "Express Mail Post Office to Addressee" services under 37 C.F.R. 1.10 on the date indicated above and is addressed to the Commissioner of Patents and Trademarks, Washington, D.C. 20231.

Typed Name of Person Mailing Paper or Fee: Crissy J. Salazar

Signature: 

**PATENT APPLICATION
DOCKET NO. 10001963-1**

MULTIPLE OUTPUT NODE CHARGE COUPLED DEVICE

INVENTOR
Oscar R. Herrera

MULTIPLE OUTPUT NODE CHARGE COUPLED DEVICE

FIELD OF THE INVENTION

- 5 This invention relates in general to optical imaging and, more particularly, to a charge coupled device having multiple output nodes.

BACKGROUND OF THE INVENTION

- 10 In the field of optical imaging, there are many types and configurations of charge coupled device (CCD) arrays. CCD arrays are composed of many light, or photon, sensing cells. Photons striking these cells cause the cells to produce an electrical charge. The charge from these cells is sequentially communicated to an analog shift register, often called a horizontal shift register or a CCD shift register.

- 15 The CCD shift register receives the charge from each cell sequentially, the image usually being read out from the left to right then top to bottom. The charge from each of the cells is stored in a register position and then output sequentially from the register to a CCD output node.

- The CCD output node holds the charge, creating a voltage differential. The voltage differential is viewed at intervals and communicated to an analog to digital converter, usually through some combination of buffers and amplifiers. The analog to digital converter digitizes the voltage to produce pixels that form an image.

- 20 One variation to this configuration is to include more than one output CCD shift register. The output CCD shift registers may be physically contiguous, or not. The multiple physically contiguous output CCD shift registers function as multiple out CCD shift registers, not a single output CCD shift register. The output CCD shift registers output charges to a like number of CCD output nodes, each out CCD shift register outputting its charge to only one CCD output node.

SUMMARY OF THE INVENTION

- 30 According to principles of the present invention, a system for optically imaging includes an array of light sensitive cells that convert light intensity to charge

proportionally, an output CCD register, two or more charge sensing nodes, and a charge demultiplexor.

According to further principles of the present invention, each cell produces an electrical charge in response to photon stimulation. The charge shift register receives the electrical charge produced by each cell and sequentially outputs the electrical charge to the charge demultiplexor. The charge demultiplexor selectively distributes the charge from each cell to one of the charge sensing nodes. The charge sensing nodes accumulate the charge until reset by a controller.

DESCRIPTION OF THE DRAWINGS

Figure 1 is a block diagram representing one embodiment of the present invention system multiple node charge coupled device.

Figure 2 is a block diagram representing an alternate embodiment of the present invention system multiple node charge coupled device.

Figure 3 is a block diagram representing another alternate embodiment of the present invention system multiple node charge coupled device.

Figure 4 is a flow chart illustrating one embodiment of a method for practicing the present invention method for producing a voltage signal segmented to represent an output of an array of cells that produce a cell electrical charge in response to photon stimulation.

Figure 5 is an illustrative timing diagram for use with the system and method of the present invention as shown in Figures 1, 2, 3, and 4.

DETAILED DESCRIPTION OF THE INVENTION

Illustrated in Figure 1 is a system 8 for optically imaging. System 8 includes an array 10 of cells, a charge shift register 12, a charge demultiplexor 14, a first charge sensing node 16, a second charge sensing node 18, output buffers 20, and analog to digital converters 22. A control system (not shown) is also required for the present invention. Control systems are well known in the art. The specific details of the control system are not important to the present invention. It is only important that

the control system is able to control elements of the present invention where necessary to ensure cooperation between the elements.

A common example of array 10 is a charge coupled device (CCD) array.

Each cell in the array of cells 10 is a light, or photon, sensing cell. The cells each produce an electrical charge in response to a photon stimulus. The more photons striking the cells, the more negative the charge produced by the cells. The electrical charge produced by each cell may be referred to as a cell electrical charge to indicate the origin of the charge and that the charge from each cell is, in most cases, isolated from the charge from the other cells.

In the figure, some of the cells are labeled with the letters A through D. These reference letters will be used to describe embodiments of the process of the present invention. Additionally, array 10 is depicted as having eight columns and six rows. The number of rows and columns was chosen for clarity and ease of reference. Array 10 may actually have any number of rows and columns and typically will have at least 800 columns and 600 rows.

Charge shift register 12 is often referred to as an output CCD shift register or a horizontal shift register. Charge shift register 12 includes charge containers 0-7. Each charge container 0-7 is able to hold one cell charge at a time. In one embodiment, charge shift register 12 receives cell charges from an entire row of cells, for example ABCDABCD. The cell charges are then shifted to one side or the other within charge shift register 12 with the end cell charge being output from charge shift register 12.

Charge shift register 12 is depicted as having eight charge containers. The number of charge containers was chosen for clarity and ease of reference. Charge shift register 12 may actually have any number of charge containers and typically will have at least 800 columns and will typically exceed the number of columns of array 10. There may also be additional charge containers between container 0 and demultiplexor 14.

Charge demultiplexor 14 is any device for receiving input from charge shift register 12 and selectively outputting to charge sensing nodes 16, 18.

Charge sensing nodes 16, 18 are often referred to as CCD nodes or output nodes. Charge sensing nodes 16, 18 are any device capable of receiving a charge from charge demultiplexor 14 and holding the charge so that the charge may be read as a voltage. For example, charge sensing nodes 16, 18 may be capacitors, or
 5 reverse biased diodes.

Only two charge sensing nodes 16, 18 are shown in Figure 1. The number of charge sensing nodes 16, 18 was chosen for clarity and ease of reference. Any number of charge sensing nodes 16, 18 greater than one may be used for the present invention.

10 Output buffers 20 are any device or combination of devices for isolating charge sensing nodes 16, 18 from analog to digital converters 22. Output buffers 20 may also include amplifiers.

Analog to digital converters 22 are any devices or combinations of devices for digitizing electrical voltage signals. These devices may contain circuitry to pre-
 15 condition the electrical signal before the digitizing process. This circuitry may include a correlated-double-sampler and gain stages.

Illustrated in Figure 2 is an alternate embodiment system 24 for optically imaging. Elements that are the same as those illustrated in Figure 1 are labeled with the same reference numbers. System 24 differs from system 8 only in that all of the
 20 output buffers 20 share the same analog to digital converter 22. A timing scheme that accounts for the shared analog to digital converter 22 must be used.

Illustrated in Figure 3 is another alternate embodiment system 26 for optically imaging. Elements that are the same as those illustrated in Figures 1 and 2 are labeled with the same reference numbers. System 26 differs from system 24 only in
 25 that all of the charge sensing nodes 16, 18 share the same output buffer 20. A timing scheme that accounts for the shared output buffer 20 must be used.

Figure 4 is a flow chart illustrating one embodiment of a method of the present invention. Array 10 is exposed to a light source such as an image. Photons from the light source strike the cells of array 10 and generate 28 cell charges. For example,
 30 cells ABCDABCD each generate 28 a cell charge. The cell charge for each cell is

independent of the cell charge for other cells in array 10. Together, the cell charges for each cell in array 10 represent the light source or image.

The cell charges are sequentially moved 30 from array 10 to charge shift register 12. In one embodiment, a whole row of charges is moved into charge shift register 12. For example, cell charges for cells ABCDABCD are moved into charge containers 0-7, respectively.

Each cell charge is sequentially read 32 out of charge shift register 12 and into demultiplexor 14. For example, cell charge A is first read out of shift register 12, then charge B, then charge C, and so on until each of the charges ABCDABCD has been read 32 out of charge shift register 12 and into demultiplexor 14. Charges from the next row of cells are then moved 30 into charge shift register 12 either after charge shift register 12 has been emptied or while charges remain in shift register 12.

As each charge is read out of shift register 12, the remaining cell charges each shift one charge towards output of shift register 12. For example, as charge A is read out of container 0, charge B is shifted from container 1 into container 0, charge C is shifted from container 2 into container 1, and so on.

Demultiplexor 14 selectively provides 34 the charges to one of the charge sensing nodes 16, 18. In one embodiment, demultiplexor 14 alternates between first charge sensing node 16 and second charge sensing node 18, providing one cell charge at a time to each node. For example, demultiplexor 14 may provide charge A to first charge sensing node 16, charge B to second charge sensing node 18, charge C to first charge sensing node 16, and charge D to second charge sensing node 18.

In alternate embodiments, demultiplexor 14 provides 34 the charges to charge sensing nodes 16, 18 as necessary to achieve the desired outcome. For example, demultiplexor 14 may provide 34 charges A, B, and C to first charge sensing node 16 and charge D to second charge sensing node 18. This pattern is useful if three out of every four charges is to be discarded and the fourth charge retained.

In one embodiment, charges are summed 36 before reading 38 the voltage from charge sensing nodes 16, 18. For example, charges A and C are summed 36

in first charge sensing node 16 and charges B and D are summed 36 in second charge sensing node 18. Any number of charges may be summed 36 before reading 38 them from charge sensing nodes 16, 18. However, care must be taken not to exceed the charge capacity of the charge sensing nodes 16, 18.

5 Once the desired number of charges has been summed 36 in charge sensing nodes 16, 18, the voltage is read from charge sensing nodes 16, 18. The voltage may be read simultaneously or consecutively from charge sensing nodes 16, 18. The voltage signal produced by reading the voltages passes through any desired buffers and amplifiers to reach analog to digital converters 22, where the voltage
10 signal is digitized 40.

One advantage to the system of the present invention is that in embodiments with two output nodes 16, 18 and two separate analog to digital converters 22, the bandwidth requirement is halved compared to conventional configurations with only one output node. The amount, or energy, of random broadcast noise added to a
15 signal being digitized depends on the square root of the bandwidth of the digitizing system. It is therefore an advantage to reduce, as much as possible, the bandwidth of the digitizing system in order to improve the signal to noise ratio. Charge binning additionally increases the signal to noise ratio by adding more than one charge packet, or cell charge, before the digitizing process.

20 Illustrated in Figure 5 is a sample timing diagram for summing charges. Signal CH1 is the voltage represented by the charge in first charge sensing node 16. Signal CH2 is the voltage represented by the charge in second charge sensing node 18. SHP is sample preset signal. SHD is a sample data signal. RST is a reset signal.

25 In operation, charge sensing nodes 16, 18 are typically reset to a preset voltage. However, the preset voltage is not always consistent. Therefore, the preset voltage signal is sampled before charge is moved to the charge sensing nodes 16, 18. After charge is moved into charge sensing nodes 16, 18, the voltage signal, now representing the data or video level, is sampled again. The difference between the
30 preset voltage signal and the data voltage signal is an accurate reflection of the charge moved to charge sensing devices 16, 18.

With reference to Figure 5, at time T0, a reset signal is present. The reset signal pulses CH1 and CH2 to a high level, which cleans charge from charge sensing nodes 16 and 18. At time T1, the reset signal is released and CH1 and CH2 both return to preset levels. At time T2, the preset signal is sampled for both CH1 and CH2.

At time T3, cell charge A (from previous examples) is put into first charge sensing node 16. Cell charge A lowers the voltage on CH1. At time T4, cell charge B is put into second node 18. Cell charge B lowers the voltage on CH2. At time T5, CH1 is lowered by charge C, thus summing cell charges A and C. At time T6, CH2 is lowered by charge D, thus summing cell charges B and D.

Summing charges is a desirable way of increasing the signal to noise ratio in optical imaging. The drawback of summing charges is the resolution of the resulting image will be reduced. If two charges are summed for each read, the resolution of the image will be halved.

At time T7, the data signal is sampled for both CH1 and CH2. A difference is obtained between the preset voltage and the data voltage. The difference is the voltage signal passed to analog to digital converters 22.

At time T8, both CH1 and CH2 are reset. The pattern continues with the next four cell charges ABCD and so on until all of the cells have been read.

The foregoing description is only illustrative of the invention. Various alternatives and modifications can be devised by those skilled in the art without departing from the invention. Accordingly, the present invention embraces all such alternatives, modifications, and variances that fall within the scope of the appended claims.

CLAIMS

What is claimed is:

- 1 1. A system for optically imaging, the system comprising:
 - 2 (a) an array of cells for producing an electrical charge in response
3 to photon stimulation;
 - 4 (b) a charge shift register configured to receive the electrical
5 charge produced by each cell in the array and to sequentially output the electrical
6 charge of each cell;
 - 7 (c) at least two charge sensing nodes for accumulating charge
8 readable as a voltage; and,
 - 9 (d) a charge demultiplexor configured to receive the output of the
10 charge shift register and to selectively distribute the output to each of the at least two
11 charge sensing nodes.
- 1 2. The system of claim 1 wherein the array of cells includes a charge
2 coupled device array.
- 1 3. The system of claim 1 further including at least one output buffer
2 configured to receive the voltage of each of the at least two charge sensing nodes.
- 1 4. The system of claim 1 further including at least one amplifier
2 configured to amplify the voltage from the at least two charge sensing nodes.
- 1 5. The system of claim 1 further including at least one analog to digital
2 converter configured to convert the voltage from the at least two charge sensing
3 nodes into a digital signal.

1 6. A method for producing a voltage signal segmented to represent an
2 output of an array of cells that produce a cell electrical charge in response to photon
3 stimulation, the method comprising:

4 (a) receiving each of the cell electrical charges from the cells in a
5 charge shift register;

6 (b) sequentially outputting the cell electrical charges from the
7 charge shift register to a charge demultiplexor;

8 (c) the charge demultiplexor selectively distributing the sequential
9 cell charges to one of at least two charge sensing nodes; and,

10 (d) sequentially reading a voltage produced by the cell charges in
11 at least one of the at least two charge sensing nodes.

1 7. The method of claim 6 wherein the charge demultiplexor selectively
2 distributing the sequential cell charges to one of at least two charge sensing nodes
3 includes the charge demultiplexor distributing one cell charge to each of the at least
4 two charge sensing nodes.

1 8. The method of claim 6 wherein the charge demultiplexor selectively
2 distributing the sequential cell charges to one of at least two charge sensing nodes
3 includes the charge demultiplexor distributing multiple cell charges to each of the at
4 least two charge sensing nodes.

1 9. A system for producing a voltage signal segmented to represent an
2 output of an array of cells that produce an electrical charge in response to photon
3 stimulation, the system comprising:

4 (a) a charge shift register configured to sequentially receive the
5 charge from each cell;

6 (b) at least two charge sensing nodes configured to accumulate
7 charge and output a voltage signal;

8 (c) a charge demultiplexor configured to sequentially distribute
9 each charge from the charge shift register to one of the at least two charge sensing
10 nodes.

1 10. The system of claim 9 further including at least one output buffer
2 configured to receive the voltage of each of the at least two charge sensing nodes.

1 11. The system of claim 9 further including at least one amplifier
2 configured to receive and amplify the voltage of each of the at least two charge
3 sensing nodes.

1 12. The system of claim 9 further including an analog to digital converter
2 configured to convert the voltage from the at least two charge sensing nodes into a
3 digital signal.

ABSTRACT

A system for optically imaging includes an array of cells, a charge shift register, two or more charge sensing nodes, and a charge demultiplexor. Each cell produces an electrical charge in response to photon stimulation. The charge shift register receives the electrical charge produced by each cell and sequentially outputs the electrical charge to the charge demultiplexor. The charge demultiplexor selectively distributes the charge from each cell to one of the charge sensing nodes. The charge sensing nodes accumulate the charge until reset by a controller.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
221




FIG. 1




FIG. 2




FIG. 3




FIG. 4

0000000000000000




FIG. 5

DECLARATION AND POWER OF ATTORNEY
FOR PATENT APPLICATIONATTORNEY DOCKET NO. 10001963-1

As a below named inventor, I hereby declare that:

My residence/post office address and citizenship are as stated below next to my name;

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled:

Multiple Output Node Charge Coupled Device

the specification of which is attached hereto unless the following box is checked:

() was filed on _____ as US Application Serial No. or PCT International Application Number _____ and was amended on _____ (if applicable).

I hereby state that I have reviewed and understood the contents of the above-identified specification, including the claims, as amended by any amendment(s) referred to above. I acknowledge the duty to disclose all information which is material to patentability as defined in 37 CFR 1.56.

Foreign Application(s) and/or Claim of Foreign Priority

I hereby claim foreign priority benefits under Title 35, United States Code Section 119 of any foreign application(s) for patent or inventor(s) certificate listed below and have also identified below any foreign application for patent or inventor(s) certificate having a filing date before that of the application on which priority is claimed:

COUNTRY	APPLICATION NUMBER	DATE FILED	PRIORITY CLAIMED UNDER 35 U.S.C. 119
N/A			YES: _____ NO: _____
			YES: _____ NO: _____

Provisional Application

I hereby claim the benefit under Title 35, United States Code Section 119(e) of any United States provisional application(s) listed below:

APPLICATION SERIAL NUMBER	FILING DATE
N/A	

U. S. Priority Claim

I hereby claim the benefit under Title 35, United States Code, Section 120 of any United States application(s) listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35, United States Code Section 112, I acknowledge the duty to disclose material information as defined in Title 37, Code of Federal Regulations, Section 1.56(a) which occurred between the filing date of the prior application and the national or PCT international filing date of this application:

APPLICATION SERIAL NUMBER	FILING DATE	STATUS (patented/pending/abandoned)
N/A		

POWER OF ATTORNEY:

As a named inventor, I hereby appoint the following attorney(s) and/or agent(s) to prosecute this application and transact all business in the Patent and Trademark Office connected therewith:

Customer Number 022879Place Customer
Number Bar Code
Label hereSend Correspondence to:
HEWLETT-PACKARD COMPANY
Intellectual Property Administration
P.O. Box 272400
Fort Collins, Colorado 80528-9599**Direct Telephone Calls To:**Steven L Webb
(970) 898-7745

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Full Name of Inventor: Oscar R Herrera E. Citizenship: HNResidence: 1836 26th Ave Greeley CO 80634Post Office Address: Same as residenceOscar R. Herrera E.
Inventor's Signature9-5-2000
Date